



**CITY OF NORTH MIAMI BEACH  
BUILDING DEPARTMENT**

**INSPECTION GUIDELINES**

**FOUNDATION GROUNDING/UNDERGROUND (COMMERCIAL)**

**ELECTRICAL**

Building permit and approved set of plans	<input type="checkbox"/>
Building permit number on the card is same as on the route	<input type="checkbox"/>
If this is not the first inspection, read inspection records and notes on permit card	<input type="checkbox"/>
Check for Notice of Commencement. FBC 105.8	<input type="checkbox"/>
Check location, size and type of connector of the equipment grounding conductors. NEC 250	<input type="checkbox"/>
Check size and type of conduits for adequate burial depth and protection, as well as suitability for location NEC Table 300.5, 300.5 (F), 310.7, 310.8, 340.10	<input type="checkbox"/>
Check service conductor warning ribbon. NEC 300.5 (D) (3)	<input type="checkbox"/>
Check backfill protection and allowances for ground movement or underground conductors and raceways. NEC 300.5 and Table 300.5	<input type="checkbox"/>



**CITY OF NORTH MIAMI BEACH  
BUILDING DEPARTMENT**

**INSPECTION GUIDELINES**

**SLAB (COMMERCIAL)**

**ELECTRICAL**

Building permit and approved set of plans	<input type="checkbox"/>
Building permit on the card is the same as on the route	<input type="checkbox"/>
If this is not the first inspection, read inspection records and notes on permit card	<input type="checkbox"/>
Check size and type of conduits for adequate burial depth and protection, as well as suitability for location. NEC Table 300.5, 300.5 (F), 310.7, 310.8, 340.10	<input type="checkbox"/>
Check service conductor warning ribbon. NEC 300.5 (D) (3)	<input type="checkbox"/>
Check backfill protection and allowances for ground movement or underground conductors and raceways. NEC 300.5 and Table 300.5	<input type="checkbox"/>



**INSPECTION GUIDELINES**

**ROUGH (COMMERCIAL)**

**ELECTRICAL**

Building permit and approved set of plans	<input type="checkbox"/>
Building permit on the card is the same as on the route	<input type="checkbox"/>
If this is not the first inspection, read inspection records and notes on permit card	<input type="checkbox"/>
<b>GENERAL WIRING METHODS</b>	
Identify the wiring methods in use and verify their suitability for the occupancy and conditions. NEC various Chapter 3 articles	<input type="checkbox"/>
Verify that all conductors of a circuit are grouped together. NEC 300.3 (B)	<input type="checkbox"/>
Check insulation values where conductors of different systems share common enclosures. NEC 300.3 (C) (1) and (2)	<input type="checkbox"/>
Check wiring methods for spacing from edges of framing and for protection from nails and screws. NEC 300.4 (A) (B) (D) and (E)	<input type="checkbox"/>
Check for insulating bushings or grommets where NM cable is installed through metal studs or conductors 4 AWG or larger enter enclosures. NEC 300.4 (B) (1) and (F)	<input type="checkbox"/>
Verify that electrical raceways and cable trays are used exclusively for electrical conductors. NEC 300.8	<input type="checkbox"/>
Check for continuity and completeness in metal raceways and enclosures. NEC 300.10	<input type="checkbox"/>
Verify that wiring methods are securely fastened in place, supported independently of suspended ceilings, and not used as supports. NEC 300.11 and applicable Chapter 3 article(s)	<input type="checkbox"/>
Check for continuity of grounded conductors in multiwire branch circuits. NEC 300.13 (B)	<input type="checkbox"/>
Check for adequate length of free conductors in boxes. NEC 300.14	<input type="checkbox"/>
Verify that boxes are installed at junction, splice, outlet, switch and pull points. NEC 300.15	<input type="checkbox"/>
Check conductor fill in raceways. NEC 300.17	<input type="checkbox"/>
Verify that raceway systems are complete prior to installation of conductors. NEC 300.18 (A)	<input type="checkbox"/>
Check vertical raceways for adequate conductor supports. NEC 300.19	<input type="checkbox"/>
Verify that fire ratings have been restored at electrical penetrations. NEC 300.21	<input type="checkbox"/>



**INSPECTION GUIDELINES**

**ROUGH (COMMERCIAL)**

**ELECTRICAL**

<p>Check installations of wiring in ducts, plenums and other air-handling spaces for proper methods and materials. NEC 300.22</p>	<p><input type="checkbox"/></p>
<p>Verify that access to equipment behind removable panels are not compromised by cables, raceways, or equipment. NEC 300.23</p>	<p><input type="checkbox"/></p>
<p><b>BOXES AND CONDUIT BODIES</b></p>	
<p>Identify wet and damp locations and the suitability of boxes and fittings. NEC 314.15</p>	<p><input type="checkbox"/></p>
<p>Check boxes and conduit bodies for adequate space for conductors. NEC 314.16</p>	<p><input type="checkbox"/></p>
<p>Verify that boxes for conductors and conduit bodies 4 AWG and larger are adequately sized. NEC 314.28</p>	<p><input type="checkbox"/></p>
<p>Verify that raceways and cables are secured to boxes. NEC 314.17 (B) and (C)</p>	<p><input type="checkbox"/></p>
<p>Check for closure of unused openings. NEC 314.17 (A)</p>	<p><input type="checkbox"/></p>
<p>Verify that boxes in walls and ceilings are flush with the finished surface or, if surfaces are noncombustible, within 1/4 in. (6 mm) of the finished surface. NEC 314.20</p>	<p><input type="checkbox"/></p>
<p>Check for excessive gaps between edges of boxes and plaster, plasterboard or drywall surfaces. NEC 314.21</p>	<p><input type="checkbox"/></p>
<p>Verify that boxes are securely fastened and supported. NEC 314.23</p>	<p><input type="checkbox"/></p>
<p>Check for covers or canopies on boxes. NEC 314.25 and 314.28 (C)</p>	<p><input type="checkbox"/></p>
<p>Check lighting fixture outlet boxes for suitability. NEC 314.27 (A) and (B)</p>	<p><input type="checkbox"/></p>
<p>Check floor boxes and receptacle/cover assemblies for listing. NEC 314.27 (C)</p>	<p><input type="checkbox"/></p>
<p>Check listing and installation of boxes used for support of ceiling-suspended (paddle) fans. NEC 314.27 (D) and 422.18</p>	<p><input type="checkbox"/></p>
<p>Verify that all boxes are accessible. NEC 314.29</p>	<p><input type="checkbox"/></p>
<p>Verify that support means for nonmetallic boxes are outside the box or otherwise isolated from contact with conductors. NEC 314.43</p>	<p><input type="checkbox"/></p>



**INSPECTION GUIDELINES**

**ROUGH (COMMERCIAL)**

**ELECTRICAL**

<b>CABINETS AND CUTOUT BOXES</b>	
Verify that cabinets and cutout boxes are suitable and properly installed in any wet or damp locations. NEC 312.2	<input type="checkbox"/>
Verify that cabinets in wall are flush with the finished surface or, if surface is noncombustible, within 1/4 in. (6 mm) of the finished surface. NEC 312.3	<input type="checkbox"/>
Check for closure of unused openings. NEC 312.5 (A)	<input type="checkbox"/>
Verify that cables are secured to cabinets and cutout boxes or that the conditions for cables with nonmetallic sheaths are met. NEC 312.5 (C)	<input type="checkbox"/>
Check wiring and bending space in cabinets and cutout boxes. NEC 312.6	<input type="checkbox"/>
Check cabinets and cutout boxes for adequate space for conductors and for splices and taps where they exist. NEC 312.7 and 312.8	<input type="checkbox"/>
<b>SWITCHES AND RECEPTACLES</b>	
Verify that all switching is done on the ungrounded conductors. NEC 404.2	<input type="checkbox"/>
Verify that switches are located not over 6 ft. 7 in. (2 m) high and that they can be operated from readily accessible places unless otherwise permitted. NEC 404.8 (A)	<input type="checkbox"/>
Verify that the voltage between adjacent grouped or ganged devices is not over 300 volts or that barriers are installed. NEC 404.8 (B)	<input type="checkbox"/>
Verify that switches or receptacles in boxes have their plaster ears seated against the wall surface or the box. NEC 404.10 (B) and 406.4 (A) and (B)	<input type="checkbox"/>
<b>SERVICES</b>	
Verify that each building or structure has only one service or, if more than one, that additional services are justified. NEC 230.2	<input type="checkbox"/>
Verify that each service drop or lateral serves only one set of service-entrance conductors or, if more than one, that the additional sets are justified. NEC 230.40	<input type="checkbox"/>
Check clearances from building openings, grade, roadway, roofs and swimming pools. NEC 230.24	<input type="checkbox"/>
Verify that the point of attachment for an overhead service drop is adequate and will provide minimum clearances. NEC 230.26, 230.27	<input type="checkbox"/>



**INSPECTION GUIDELINES**

**ROUGH (COMMERCIAL)**

**ELECTRICAL**

Verify that masts used as support for service-drop conductors have adequate strength and are not used to support other conductors or equipment. NEC 230.28	<input type="checkbox"/>
Verify that support for service conductors passing over a roof are adequate and substantial. NEC 230.29	<input type="checkbox"/>
Check above-ground conductors and cables for adequate support and protection from physical damage. NEC 230.50, 230.51	<input type="checkbox"/>
Verify that wiring methods or support system for service-entrance conductors are suitable. NEC 230.43, 230.44, 230.202	<input type="checkbox"/>
Verify that service raceways are arranged to drain and that service heads are raintight and properly located. NEC 230.53, 230.54	<input type="checkbox"/>
Check service conductors for adequate size and rating. NEC 230.23, 230.31, 230.42	<input type="checkbox"/>
Verify that service equipment is identified as suitable for the use. NEC 230.66	<input type="checkbox"/>
Verify that a service disconnecting means is provided, suitable, marked and located outside or inside nearest the point of entrance of the service conductors. NEC 230.70	<input type="checkbox"/>
Verify that service overcurrent protection is provided, properly sized, and part to or adjacent to the disconnecting means. NEC 230.90, 230.91	<input type="checkbox"/>
Verify that service disconnects are grouped together and limited to six in any one location. NEC 230.71, 230.72	<input type="checkbox"/>
Check ratings of service disconnecting means. NEC 230.79, 230.80	<input type="checkbox"/>
Check for equipment connected to the supply side of the service disconnecting means and overcurrent protection. NEC 230.82, 230.94	<input type="checkbox"/>
<b>FEEDERS</b>	
Verify that feeders are at least equal to the minimum required size. NEC 215.2	<input type="checkbox"/>
Verify that feeder conductors, including any neutral conductors, are adequate for the load. NEC 220.40, 220.80	<input type="checkbox"/>
Check overcurrent device and feeder conductor sizing for continuous and noncontinuous loads. NEC 220.60, 215.3	<input type="checkbox"/>
Check feeders with disconnecting means rated at 1000 A or greater for GFP for equipment if required. NEC 215.10, 230.95	<input type="checkbox"/>



**INSPECTION GUIDELINES**

<b>ROUGH (COMMERCIAL)</b>	<b>ELECTRICAL</b>
Verify that disconnects are provided at separate structures for feeders running between structures. NEC Article 225, Part II	<input type="checkbox"/>
Verify that disconnects at separate structures are properly rated, located, grouped and identified. NEC Article 225, Part II	<input type="checkbox"/>
Verify that any outside feeders use appropriate wiring methods and are properly supported and arranged to drain. NEC 225.10 and 225.20 through 225.22	<input type="checkbox"/>
Check any outside feeders for adequate supports, clearances and mechanical protection. NEC 225.15 through 225.20	<input type="checkbox"/>
Verify that feeders tapped from transformers are properly protected by overcurrent devices. NEC 240.4 (E) and (F), 240.21 (C)	<input type="checkbox"/>
Check panelboards supplying or supplied by feeders for overcurrent protection, grounding, proper enclosures, and number of overcurrent devices. NEC 408.36 through 408.41	<input type="checkbox"/>
<b>BRANCH CIRCUITS</b>	
Verify that wiring methods used are appropriate for the conditions and occupancy. NEC Chapter 3	<input type="checkbox"/>
Check panelboards for proper overcurrent protection and limitations on number of overcurrent devices. NEC 408.36 through 408.54	<input type="checkbox"/>
Check individual and multiwire branch circuits for proper ratings. NEC 210.3	<input type="checkbox"/>
Check conductors and overcurrent protection for consideration of continuous and noncontinuous loads, multioutlet loads, and minimum ampacity and size. NEC 210.19, 210.20	<input type="checkbox"/>
Check branch circuits supplying receptacles and other outlet devices for permitted ratings of circuits and receptacles. NEC 210.21, 210.24	<input type="checkbox"/>
Verify that branch-circuit loads do not exceed maximum permitted loads. NEC 220.10	<input type="checkbox"/>
Verify that branch circuits supplying motors are sized according to Article 430 or 440 and that inductive lighting loads are based on ballast ratings. NEC 220.18	<input type="checkbox"/>
Verify that branch circuits are used to supply only permissible loads based on their ratings. NEC 210.23	<input type="checkbox"/>
Verify that the number of branch circuits is adequate and that the load is evenly proportioned among the branch circuits. NEC 210.11	<input type="checkbox"/>
Check for compliance with branch-circuit voltage limitations. NEC 210.6	<input type="checkbox"/>



**INSPECTION GUIDELINES**

<b>ROUGH (COMMERCIAL)</b>	<b>ELECTRICAL</b>
Verify that branch circuits for specific loads meet the requirements of the applicable articles. NEC 210.2	<input type="checkbox"/>
Check for proper use and identification of multiwire branch circuits. NEC 210.4, 210.5 (C)	<input type="checkbox"/>
Check for required receptacles and lighting at mechanical equipment. NEC 210.63, 210.70 (C)	<input type="checkbox"/>
Check for required outlets or receptacles for show windows and signs. NEC 210.62, 600.5 (A)	<input type="checkbox"/>
Verify that receptacles are provided for all cord-and plug-connected appliances, and where flexible cords are used. NEC 210.50	<input type="checkbox"/>
Verify that GFCI protection is provided for receptacles in bathrooms, in kitchens, and on rooftops other than dwelling units. NEC 210.8 (B)	<input type="checkbox"/>
Verify that disconnects are provided at separate structures for branch circuits running between structures. NEC Article 225, Part II, 225.31, 225.32 and 225.33	<input type="checkbox"/>
Check for adequate size and clearances for outside branch circuits. NEC 225.6, 225.18, 225.19	<input type="checkbox"/>
<b>SERVICE GROUNDING AND BONDING</b>	<input type="checkbox"/>
Determine what grounding electrodes are available on the premises. NEC 250.50, 250.52 (A) (1) through (8)	<input type="checkbox"/>
Determine which other electrodes are required or used. NEC 250.52 (A) (1) through (8)	<input type="checkbox"/>
Verify that the grounding electrode conductor or conductors are properly sized. NEC 250.66, 250.64 (F)	<input type="checkbox"/>
Verify that the grounding electrode conductors are protected and secured. NEC 250.64 (A) and (B)	<input type="checkbox"/>
Verify that grounding electrode conductor enclosures are properly bonded. NEC 250.64 (E)	<input type="checkbox"/>
Verify that grounding electrode conductor is either unspliced or spliced using appropriate methods. NEC 250.64 (C)	<input type="checkbox"/>
Check for correct size and installation of any rod or pipe electrodes. NEC 250.52, 250.53 (G)	<input type="checkbox"/>
Verify the accessibility of grounding electrode conductor connections. NEC 250.68 (A)	<input type="checkbox"/>
Check for proper grounding electrode conductor connections, including buried connections. NEC 250.70, 250.68	<input type="checkbox"/>



**INSPECTION GUIDELINES**

<b>ROUGH (COMMERCIAL)</b>	<b>ELECTRICAL</b>
Verify that metal water pipe is bonded. NEC 250.104 (A)	<input type="checkbox"/>
Verify that exposed structural building frames are bonded. NEC 250.104 (C)	<input type="checkbox"/>
Check for proper size and length of bonding jumpers around water meters and the like. NEC 250.66, 250.68 (B), 250.104 (A)	<input type="checkbox"/>
Check the size, type and installation of the main bonding jumper. NEC 250.28	<input type="checkbox"/>
Verify appropriate grounding methods for equipment fastened in place or connected by permanent wiring methods. NEC 250.134, 250.136	<input type="checkbox"/>
Verify appropriate types of equipment grounding conductors. NEC 250.118	<input type="checkbox"/>
Check separate equipment grounding conductors for proper sizing and identification. NEC 250.122, 250.119	<input type="checkbox"/>
Check connections of equipment grounding conductors within outlet boxes. NEC 250.146, 250.148	<input type="checkbox"/>
Verify that proper methods are used to bond receptacles to boxes. NEC 250.146, 250.8	<input type="checkbox"/>
Check installation of equipment bonding jumpers, especially where flexible connections of cords are used. NEC 250.96, 250.102, 350.60, 348.60	<input type="checkbox"/>
Verify grounding of panelboards and connections of equipment grounding conductors to panelboards. NEC 408.40, 408.41	<input type="checkbox"/>
Verify proper grounding at separate buildings or structures. NEC 250.32 (B) (1) (2)	<input type="checkbox"/>
Check equipment grounding of electrical ranges and clothes dryers. NEC 250.140, 250.142	<input type="checkbox"/>
Verify bonding of raceways and cable sheaths containing circuits operating at over 250 volts to ground. NEC 250.97	<input type="checkbox"/>
Check installations with isolated grounding conductors for proper connections and for grounding of the associated enclosures and wiring methods. 250.146 (D), 250.96 (B), 406.2 (D), 408.40	<input type="checkbox"/>
Check for occupancies or equipment with special grounding or bonding requirements. NEC 250.4	<input type="checkbox"/>
<b>WHEELCHAIR ACCESSIBILITY</b>	
Forward reach for wheelchairs; verify receptacles no lower than 15" AFF, no higher than 48" AFF. FBC 11-4.2.5	<input type="checkbox"/>



**CITY OF NORTH MIAMI BEACH  
BUILDING DEPARTMENT**

**INSPECTION GUIDELINES**

**ROUGH (COMMERCIAL)**

**ELECTRICAL**

Clear side reach for wheelchair, verify receptacles no lower than 9" AFF, no higher than 54" AFF. FBC 11-4.2.6

Maximum forward reach with obstruction less than 20" into space: 48" AFF. FBC 11 Figure 5(b)

Maximum forward reach with obstruction between 20" to 25" in o space: 44" AFF. FBC 11 Figure 5(b)

Maximum side-reach with obstruction 34" high and 24" wide: 46" AFF. FBC 11 Figure 6



**INSPECTION GUIDELINES**

**FINAL (COMMERCIAL)**

**ELECTRICAL**

Building permit and approved set of plans	<input type="checkbox"/>
Building permit on the card is the same as on the route	<input type="checkbox"/>
If this is not the first inspection, read inspection records and notes on permit card	<input type="checkbox"/>
Verify that all devices, luminaries and equipment are installed and secured as shown on the approved plans	<input type="checkbox"/>
<b>CABINETS AND CUTOUT BOXES</b>	
Verify that cabinets and cutout boxes are suitable and properly installed in any wet or damp locations. NEC 312.2	<input type="checkbox"/>
Verify that cabinets in wall are flush with the finished surface or, if surface is noncombustible, within 1/4 in. (6 mm) of the finished surface. NEC 312.3	<input type="checkbox"/>
<b>SWITCHES AND RECEPTACLES</b>	
Verify that any switches in wet locations are properly installed in weatherproof enclosures. NEC 404.4	<input type="checkbox"/>
Verify that switches are located not over 6 ft. 7 in. (2 m) high and that they can be operated from readily accessible places unless otherwise permitted. NEC 404.8 (A)	<input type="checkbox"/>
Verify that metal switch boxes, switches and any metal faceplates are grounded. NEC 404.9 (B) and 404.12	<input type="checkbox"/>
Verify that switches and receptacles are used within their ratings. NEC 404.14, 406.2 (A) and 430.109	<input type="checkbox"/>
Verify that general-use dimmers are installed only for control of permanently installed incandescent lighting. NEC 404.14 (E)	<input type="checkbox"/>
Check listing and marking of any switches or receptacles used with aluminum conductors. NEC 404.14 (C), 406.2 (C) and 110.14	<input type="checkbox"/>
Check receptacles in wet or damp locations for proper covers and enclosures. NEC 406.8	<input type="checkbox"/>
Verify that isolated ground receptacles are properly identified and connected to isolated grounding conductors. NEC 406.2 (D)	<input type="checkbox"/>
Check the receptacles project from metal faceplates or are flush with nonmetallic faceplates and that the faceplates cover openings. NEC 406.4 (D)	<input type="checkbox"/>
Check receptacles for proper polarity and for grounding and bonding connections. NEC 406.3, 250.146, and 200.11	<input type="checkbox"/>
Verify that receptacle ratings and branch-circuit ratings are compatible. NEC 210.21 and 210.24	<input type="checkbox"/>



**INSPECTION GUIDELINES**

FINAL (COMMERCIAL)	ELECTRICAL
<b>SERVICES</b>	
Verify that each building or structure has only the one service or, if more than one, that additional services are justified. NEC 230.2	<input type="checkbox"/>
Verify that each service drop or lateral serves only one set of service-entrance conductors or, if more than one, that the additional sets are justified. NEC 230.40	<input type="checkbox"/>
Check clearances from building openings, grade, roadway, roofs and swimming pools. NEC 230.24	<input type="checkbox"/>
Verify that the point of attachment for an overhead service drop is adequate and will provide minimum clearances. NEC 230.26, 230.27	<input type="checkbox"/>
Verify that masts use as support for service-drop conductors have adequate strength and are not used to support other conductors or equipment. NEC 230.28	<input type="checkbox"/>
Verify that support for service conductors passing over a roof are adequate and substantial. NEC 230.29	<input type="checkbox"/>
Verify that service equipment is identified as suitable for the use. NEC 230.66	<input type="checkbox"/>
Verify that a service disconnecting means is provided, suitable, marked and located outside or inside nearest the point of entrance of the service conductors. NEC 230.70	<input type="checkbox"/>
Verify that service overcurrent protection is provided, properly sized, and part to or adjacent to the disconnecting means. NEC 230.90, 230.91	<input type="checkbox"/>
Verify that service disconnects are grouped together and limited to six in any one location. NEC 230.71, 230.72	<input type="checkbox"/>
Check ratings of service disconnecting means. NEC 230.79, 230.80	<input type="checkbox"/>
<b>BRANCH CIRCUITS</b>	
Check for required receptacles and lighting at mechanical equipment. NEC 210.63, 210.70 (C)	<input type="checkbox"/>
Check for required outlets or receptacles for show windows and signs. NEC 210.62, 600.5 (A)	<input type="checkbox"/>
Verify that GFCI protection is provided for receptacles in bathrooms, in kitchens, and on rooftops other than dwelling units. NEC 210.8 (B)	<input type="checkbox"/>
Verify that disconnects are provided at separate structures for branch circuits running between structures. NEC Article 225, Part 11, 225.31, 225.32 and 225.33	<input type="checkbox"/>



**INSPECTION GUIDELINES**

<b>FINAL (COMMERCIAL)</b>	<b>ELECTRICAL</b>
<b>SERVICE GROUNDING AND BONDING</b>	
Verify that the grounding electrode conductor or conductors are properly sized. NEC 250.66, 250.64 (F)	<input type="checkbox"/>
Verify that the grounding electrode conductors are protected and secured. NEC 250.64 (A) and (B)	<input type="checkbox"/>
Check for correct size and installation of any rod or pipe electrodes. NEC 250.52, 250.53 (G)	<input type="checkbox"/>
Verify that metal water pipe is bonded. NEC 250.104 (A)	<input type="checkbox"/>
Verify that exposed structural building frames are bonded. NEC 250.104 (C)	<input type="checkbox"/>
Check for proper size and length of bonding jumpers around water meters and the like. NEC 250.66, 250.68 (B), 250.104 (A)	<input type="checkbox"/>
Check separately derived systems for proper grounding electrodes, grounding electrode conductors and bonding jumpers. NEC 250.30 (A)	<input type="checkbox"/>
<b>EQUIPMENT GROUNDING AND BONDING</b>	
Check for occupancies or equipment with special grounding or bonding requirements. NEC 250.3	<input type="checkbox"/>
<b>WHEELCHAIR ACCESSIBILITY</b>	
Forward reach for wheelchairs, verify receptacles no lower than 15" AFF, no higher than 48" AFF. FBC 11-4.2.5	<input type="checkbox"/>
Clear side reach for wheelchair, verify receptacles no lower than 9" AFF, no higher than 54" AFF. FBC 11-4.2.6	<input type="checkbox"/>
Maximum forward reach with obstruction less than 20" into space: 48" AFF. FBC 11 Figure 5(b)	<input type="checkbox"/>
Maximum forward reach with obstruction between 20" to 25" in o space: 44" AFF. FBC 11 Figure 5(b)	<input type="checkbox"/>
Maximum side-reach with obstruction 34" high and 24" wide: 46" AFF. FBC 11 Figure 6	<input type="checkbox"/>